


Please type a plus sign (+) inside this box (+)



PTO/SB/08A (08-00)

Approved for use through 10/31/2002. OMB 0651-0031

U.S. Patent and Trademark Office: U.S. DEPARTMENT OF COMMERCE

Under the Paperwork Reduction Act of 1995, no person is required to respond to a collection of information unless it contains a valid OMB control number.

Substitution for form 1449-A/PTO INFORMATION DISCLOSURE STATEMENT BY APPLICANT (use as many sheets as necessary)		Complete if Known Application Number: 09/688,216 Filing Date: October 16, 2000 First Named Inventor: Knud Erik BÆJGAARD et al. Group Art Unit: 2643 Examiner Name: Unknown Attorney Docket Number: 740119-98	
Sheet	1	of	1

U.S. PATENT DOCUMENTS					
Examiner Initials ¹	Cite No. ¹	U.S. Patent Document		Name of Patent or Applicant of Cited Document	Date of Publication of Cited Document MM-DD-YYYY
		Number	Kind Code ² (if known)		
KAS		4,425,481		Mansgold et al.	01-1984
		4,598,417		Deno	07-01-1986
		5,481,615		Eatwell et al.	01-1996
		5,539,831		Harley	07-1996
		5,602,924		Durand et al.	02-1997
		4,594,731		Lewkowicz	06-10-1986
		4,783,814		Foley	11-08-1988
		5,003,605		Phillipps et al.	03-26-1991

RECEIVED

JUN 21 2001

Technology Center 2600

FOREIGN PATENT DOCUMENTS						
Examiner Initials ¹	Cite No. ¹	Foreign Patent Document		Name of Patent or Applicant of Cited Document	Date of Publication of Cited Document MM-DD-YYYY	Pages, Columns, Lines, Where Relevant Paragraphs or Relevant Figures Appear
		Office ³	Number ³			

OTHER PRIOR ART - NON PATENT LITERATURE DOCUMENTS			
Examiner Initials ¹	Cite No. ¹	Include name of the author (in CAPITAL LETTERS), title of the article (when appropriate), title of the item (book, magazine, journal, serial, symposium, catalog, etc.), date, page(s), volume-issue number(s), publisher, city and/or country where published.	1 ²
KAS		HRTF MEASUREMENTS OF A KEMAR DUMMY-HEAD MICROPHONE, BILL GARDNER ET AL., MIT MEDIA LAB, HTTP://sound.media.mit.edu/KEMAR/hrtfdoc.txt, August 8, 2000, 9 pages	

Examiner Signature: Laura A. Green	Date Considered: 8-20-02
------------------------------------	--------------------------

*EXAMINER: Initial if reference considered, whether or not citation is in conformance with MPEP 609. Draw line through citation if not in conformance and not considered. Include copy of this form with next communication to applicant.

¹ Unique citation designation number. ² See attached Kinds of U.S. Patent Documents. ³ Enter Office that issued the document, by the two-letter code (WIPO Standard ST.3). ⁴ For Japanese patent documents, the indication of the year of the reign of the Emperor must precede the serial number of the patent document. ⁵ Kind of document by the appropriate symbols as indicated on the document under WIPO Standard ST.16 if possible. ⁶ Applicant is to place a check mark here if English language Translation is attached.

¹ Unique citation designation number. ² Applicant is to place a check mark here if English language Translation is attached.

Burden Hour Statement: This form is estimated to take 2.0 hours to complete. Time will vary depending upon the needs of the individual case. Any comments on the amount of time you are required to complete this form should be sent to the Chief Information Officer, U.S.


NVA29571.1

HRTF Measurements of a KEMAR Dummy-Head Microphone

Bill Gardner and Keith Martin
MIT Media Lab

Abstract:

An extensive set of head-related transfer function (HRTF) measurements of a KEMAR dummy head microphone was completed in May, 1994. The measurements consist of the left and right ear impulse responses from a Realistic Optimus Pro 7 loudspeaker mounted 1.4 meters from the KEMAR. Maximum length (ML) pseudo-random binary sequences were used to obtain the impulse responses at a sampling rate of 44.1 kHz. A total of 710 different positions were sampled at elevations from -40 degrees to +90 degrees. Also measured were the impulse response of the speaker in free field and several headphones placed on the KEMAR. This data is being made available to the research community on the Internet via anonymous FTP and the World Wide Web.



(48K)

Keith, KEMAR, and Bill in MIT's anechoic chamber.

The ftp and html archive is maintained by Bill Gardner, billg@media.mit.edu and Keith Martin, kdm@media.mit.edu. It contains a set of head-related transfer function (HRTF) measurements of a KEMAR dummy-head microphone and related software.

The archive contains:

[README \(1K\)](#) - A brief description of the archive

[KEMAR-FAQ.txt \(25K\)](#) - Frequently Asked Questions - read this

[compact.tar.Z \(200K\)](#) - Compact HRTF measurements

[compact.zip \(226K\)](#) - Compact HRTF measurements, Windows zip file

[full.tar.Z \(1.3M\)](#) - Complete set of HRTF measurements, speaker and headphone responses

[full.zip \(1.4M\)](#) - Complete set of HRTF measurements, Windows zip file

[headphones+spkr.zip \(41K\)](#) - Speaker and headphone responses, Windows zip file

[hrtfdoc.ps \(116K\)](#) - Postscript documentation on the HRTF data

<http://sound.media.mit.edu/KEMAR.html>

8/8/2000

[hrtfdoc.txt \(18K\)](#) - Text-only version of hrtfdoc.ps

[diffuse.tar.Z \(197K\)](#) - diffuse-field equalized HRTFs (44.1 kHz)

[diffuse.zip \(221K\)](#) - diffuse-field equalized HRTFs (44.1 kHz), Windows zip file

[diffuse32k.tar.Z \(157K\)](#) - above resampled to 32kHz sampling rate

[3Daudio.tar.Z \(203K\)](#) - demonstration 3D audio spatializer for SGI Indigos

[matlab_scripts.tar.Z \(11K\)](#) - useful MATLAB scripts for processing data

The file hrtfdoc contains a detailed description of the data and the measurement technique. It is also available online as an html document ([hrtfdoc.html](#)). It may also be obtained through the Media Lab as Perceptual Computing Technical Report #280. Note that the diffuse-field equalized HRTFs, 3D audio program, MATLAB scripts, and Windows zip format files were added to this archive after the documentation was written.

The Windows zip format files were generously provided by Robert Cain.

This data is Copyright 1994 by the MIT Media Laboratory. It is provided free with no restrictions on use, provided the authors are cited when the data is used in any research or commercial application.

Bill Gardner hillg@media.mit.edu and Keith Martin kdm@media.mit.edu

MIT Media Lab Machine Listening Group

May 18, 1994 (last revised July 18, 2000)

<http://sound.media.mit.edu/KEMAR.html>

8/8/2000

HRTF Measurements of a KEMAR Dummy-Head Microphone
MIT Media Lab Perceptual Computing - Technical Report #280

Bill Gardner and Keith Martin
MIT Media Lab
May, 1994

abstract

An extensive set of head-related transfer function (In this document, we use the acronym HRTF to refer to head related impulse responses. The impulse response and transfer function are related in the obvious way by the Fourier transform.) measurements of a KEMAR dummy head microphone has recently been completed. The measurements consist of the left and right ear impulse responses from a Realistic Optimus Pro 7 loudspeaker mounted 1.4 meters from the KEMAR. Maximum length (ML) pseudo-random binary sequences were used to obtain the impulse responses at a sampling rate of 44.1 kHz. In total, 710 different positions were sampled at elevations from -40 degrees to +90 degrees. Also measured were the impulse response of the speaker in free field and several headphones placed on the KEMAR. This data is being made available to the research community on the Internet via anonymous FTP and the World Wide Web.

Measurement technique

Measurements were made using a Macintosh Quadra computer equipped with an Audiomeia II DSP card, which has 16-bit stereo A/D and D/A converters that operate at a 44.1 kHz sampling rate. One of the audio output channels was sent to an amplifier which drove a Realistic Optimus Pro 7 loudspeaker. This is a small two way loudspeaker with a 4 inch woofer and 1 inch tweeter. The KEMAR, Knowles Electronics model DB-4004, was equipped with model DB-061 left pinna, model DB-065 (large red) right pinna, Etymotic ER-11 microphones, and Etymotic ER-11 preamplifiers. The outputs of the microphone preamplifiers were connected to the stereo inputs of the Audiomeia card.

From the standpoint of the Audiomeia card, a signal sent to the audio outputs results in a corresponding signal appearing at the audio inputs. Measuring the impulse response of this system yields the impulse response of the combined system consisting of the Audiomeia D/A and A/D converters and anti-alias filters, the amplifier, the speaker, the room in which the measurements are made, and most importantly, the response of the KEMAR with its associated microphones and preamps. We can avoid interference due to room reflections by ensuring that any reflections occur well after the head response time, which is several milliseconds. We can compensate for a non-uniform speaker response by measuring the speaker response separately and creating an inverse filter. The inverse filter, when applied to an HRTF measurement, equalizes the speaker response to be flat.

The impulse responses were obtained using ML sequences (for a detailed description of the ML sequence measurement technique, see [2]). The sequence length was $N = 16383$ samples, corresponding to a 14-bit generating register. Two copies of the sequence were concatenated to form a $2*N$ sample sound which was played from the Audiomeia card. Simultaneously, $2*N$ samples were recorded on both the left and right input channels (we wrote software for the Audiomeia to simultaneously play and record stereo sounds). For each input channel, the following

<http://sound.media.mit.edu/KEMAR/hrtfdoc.txt>

8/8/2000

technique was used to recover the impulse response. The first N samples of the result were discarded, and the remaining N samples were duplicated to form a $2*N$ sample sequence. This was cross-correlated with the original N sample ML sequence using FFT based block convolution, forming a $3*N - 1$ sample result. The N sample impulse response was extracted starting at $N - 1$ samples into this result.

Noise in the ML sequence impulse responses can be attributed to measurement noise, non-linearities in the system, and time aliasing. Measurement noise can be averaged out by using longer ML sequences. This is completely analogous to averaging smaller length measurements. For instance, averaging two independent N point impulse response measurements should achieve a 3 dB signal to noise ratio (SNR) improvement over either of the measurements considered alone. Similarly, using a $2*N(+1)$ point ML sequence should achieve a 3 dB SNR improvement over using an N point ML sequence. However, noise caused by non-linearities in the system will not be reduced by repeated averaging over ML sequence measurements, because the noise is correlated between measurements. It is necessary either to use longer ML sequences or to average the responses resulting from different ML sequences (i.e. from different masks) to reduce noise caused by non-linearities (see [3]). Time aliasing can be eliminated by using ML sequences which are longer than the reverberation time of the measurement space. Since the measurements were done in an anechoic chamber and the ML sequences were sufficiently long, time aliasing was not a problem. We chose 16383 point measurements to give good signal to noise ratios without excessive storage requirements or computation time. The measured SNR was 65 dB, as discussed later.

Measurement procedure

The measurements were made in MIT's anechoic chamber. The KEMAR was mounted upright on a motorized turntable which could be rotated accurately to any azimuth under computer control. The speaker was mounted on a boom stand which enabled accurate positioning of the speaker to any elevation with respect to the KEMAR. Thus, the measurements were made one elevation at a time, by setting the speaker to the proper elevation and then rotating the KEMAR to each azimuth. With the KEMAR facing forward toward the speaker (0 degrees azimuth), the speaker was positioned such that a normal ray projected from the center of the face of the speaker bisected the interaural axis of the KEMAR at a distance of 1.4 meters. This was accomplished using a tape measure, plumb line, calculator, a 1.4 meter rod, and a fair amount of eyeballing. We believe the speaker was always within 0.5 inch of the desired position, which corresponds to an angular error of ± 0.5 degrees.

The spherical space around the KEMAR was sampled at elevations from -40 degrees (40 degrees below the horizontal plane) to +90 degrees (directly overhead). At each elevation, a full 360 degrees of azimuth was sampled in equal sized increments. The increment sizes were chosen to maintain approximately 5 degree great-circle increments. The table below shows the number of samples and azimuth increment at each elevation (all angles in degrees). A total of 710 locations were sampled.

Elevation	Number of Measurements	Azimuth Increment
-40	56	6.43

<http://sound.media.mit.edu/KEMAR/hrtfdoc.txt>

8/8/2000

-30	60	6.00
-20	72	5.00
-10	72	5.00
0	72	5.00
10	72	5.00
20	72	5.00
30	60	6.00
40	56	6.43
50	45	8.00
60	36	10.00
70	24	15.00
80	12	30.00
90	1	x.xx

Table 1: Number of measurements and azimuth increment at each elevation

If the KEMAR was perfectly symmetrical and its ear microphones were identical, we would only need to sample either the left or right hemisphere around the KEMAR. However, our KEMAR had two different pinnae (the left pinna was ``normal'', the right pinna was the ``large red'' model), and consequently the responses were not identical. This was actually a bonus, because by sampling the entire sphere we obtained two complete sets of symmetrical HRTFs.

Speaker and headphone measurements

The impulse response of the Optimus Pro 7 speaker was measured in the anechoic chamber using a Neumann KMi 84 microphone at a distance of 1.4 meters. The measurement technique was exactly the same as the HRTF measurements. The speaker impulse response can be used to create an inverse filter to equalize the HRTF measurements, as will be discussed later.

In addition to measuring the speaker response, we also measured a variety of headphones placed on the KEMAR. The headphones measured are listed in Table 2.

AKG K240	Circumaural, closed earcups, but not well isolated.
Sennheiser HD480	Supraaural, open air.
Radio Shack Nova 38	Supraaural, walkman style.
Sony Twin Turbo	Intraaural, earplug style.

Table 2: Description of headphones measured

It is possible the HRTF data will be used to create a spatial auditory display, in which case the frequency response of the headphones used to render the display is important. The above headphone responses may be useful to create appropriate inverse filters. We did not gather data on the repeatability of such measurements (i.e. how much variation in the frequency response is expected each time the headphones are placed on the head).

The data

As described earlier, each HRTF measurement yielded a 16383 point impulse response at a 44.1 kHz sampling rate. Most of this data is irrelevant. The 1.4 meter air travel corresponds to approximately 180 samples, and there is an additional delay of 50 samples inherent in

the playback/recording system. Consequently, in each impulse response, there is a delay of approximately 230 samples before the head response occurs. The head response persists for several hundred samples (subject to interpretation) and is followed by various reflections off objects in the anechoic chamber (such as the KEMAR turntable). In order to reduce the size of the data set without eliminating anything of potential interest, we decided to discard the first 200 samples of each impulse response and save the next 512 samples. Each HRTF response is thus 512 samples long. Most researchers will no doubt truncate this data further.

The impulse responses are stored as 16-bit signed integers, with the most significant byte stored in the low address (i.e. Motorola 68000 format). The dynamic range of the 16-bit integers (96 dB) exceeds the signal to noise ratio of the measurements, which we conservatively measured to be 65 dB. Using the 0 degree elevation, 0 degree azimuth, left ear, 16383 point measurement, we compared the energy in 100 samples centered on the head response to the first 100 samples of the response (these should ideally be zero) which yielded the 65 dB SNR.

The HRTF data is stored in directories by elevation. Each directory name has the format ``elevEE'', where EE is the elevation angle. Within each directory each filename has the format ``XEEeAAAa.dat'' where X is either ``L'' or ``R'' for left and right ear response, respectively, EE is the elevation angle of the source in degrees, from -40 to 90, and AAA is the azimuth of the source in degrees, from 0 to 355. Elevation and azimuth angles indicate the location of the source relative to the KEMAR, such that elevation 0 azimuth 0 is directly in front of the KEMAR, elevation 90 is directly above the KEMAR, elevation 0 azimuth 90 is directly to the right of the KEMAR, etc. For example, the file ``R-20e270a.dat'' is the right ear response, with the source 20 degrees below the horizontal plane and 90 degrees to the left of the head. Note that three digits are always given for azimuth so that the files appear in sorted order in each directory.

To select a pair of HRTF responses, we recommend using symmetrical responses obtained from one of the KEMAR ears. For instance, for the HRTF responses for a source 45 degrees to the right of the head at 0 degrees elevation, use ``L0e045a.dat'' for the left ear and ``L0e315a.dat'' for the right ear, or use ``R0e315a.dat'' for the left ear and ``R0e045a.dat'' for the right ear. Note that this approach eliminates binaural localization cues in the median plane.

The maximum sample value in the left ear HRTF data is -26793 in file ``L40e289a.dat''. In the right ear HRTF data the maximum value is 29877 in the file ``R40e039a.dat''.

The speaker impulse response and headphone impulse responses are stored in the directory ``headphones+spkr''. An inverse filter for the Optimus Pro 7 speaker is included. The inverse filter was designed by zero-padding the measured impulse response and taking the DFT of the zero-padded sequence. The resulting complex spectrum was inverted by negating the phase and inverting the magnitude. This was done over the range from DC to 18 kHz; beyond 18 kHz the inverse spectrum was made flat by repeating the 18 kHz magnitude value. The inverse filter was obtained by computing the inverse DFT of this spectrum. A minimum phase version of this inverse filter was also computed using the real cepstrum (see [1]). The files in the ``headphones+spkr'' directory are listed in Table 3.

filename	description
Optimus.dat	Optimus Pro 7 impulse response
Opti_inverse.dat	Inverse filter for Optimus Pro 7
Opti_minphase.dat	Minimum phase inverse filter
AKG-K240-L.dat	AKG headphone impulse response
AKG-K240-R.dat	
Senn-HD480-L.dat	Sennheiser headphone impulse response
Senn-HD480-R.dat	
RS-Nova38-L.dat	Radio Shack headphone impulse response
RS-Nova38-R.dat	
Sony-TwinTurbo-L.dat	Sony headphone impulse response
Sony-TwinTurbo-R.dat	

Table 3: Contents of ``headphones+spkr`` directory

The 512 point impulse responses and speaker and headphone data may be found in the tar archive ``full.tar.Z``.

Compact data files

For those interested purely in 3-D audio synthesis, we have included a data-reduced set of 128 point symmetrical HRTFs derived from the left ear KEMAR responses. These have also been equalized to compensate for the non-uniform response of the Optimus Pro 7 speaker. The 128 point responses may be found in the tar archive ``compact.tar.Z``. The data-reduced impulse responses are stored in directories by elevation as described above. Within each directory each filename has the format ``HEEEAAAa.dat`` where EE is the elevation angle of the source in degrees, and AAA is the azimuth angle of the source in degrees.

Each file contains a stereo pair of 128 point impulse responses corresponding to the left and right ear responses for the given source position. For instance, the file ``H0e090a.dat`` contains the left and right ear impulse responses for a source directly to the right of the listener. The left response was derived from the 512 point file ``L0e090a.dat`` and the right response was derived from the 512 point file ``L0e270a.dat``. The data is stored as 16-bit integers and the stereo samples are stored in (left, right) interleaved order. Each 128 point response was obtained by convolving the appropriate 512 point impulse responses with the minimum phase inverse filter for the Optimus Pro 7 speaker. The resulting impulse responses were then cropped by retaining 128 samples starting at sample index 26. The maximum sample value in the 128 point data is 30496 in the file ``H-10e100a.dat``.

Accessing the data on the Internet

The data is organized into two tar archives, this document (postscript and plain text) and a text README file. The structure of the tar archives is described in the previous sections.

To retrieve the HRTF data by anonymous FTP, your FTP session would look something like the following:

```
kdm@eno:~ > ftp sound.media.mit.edu
Connected to sound.media.mit.edu.
220 sound.media.mit.edu FTP server (ULTRIX Version 4.1 Tue Mar 19 00:38:17 EST 1991
Name (sound.media.mit.edu:kdm): anonymous
331 Guest login ok, send ident as password.
```

<http://sound.media.mit.edu/KEMAR/hrtfdoc.txt>

8/8/2000


```

Password: {Type your User ID here}
230 Guest login ok, access restrictions apply.
ftp> cd pub
250 CWD command successful.
ftp> cd Data
250 CWD command successful.
ftp> cd KEMAR
250 CWD command successful.
ftp> ls
200 PORT command successful.
150 Opening data connection for /bin/ls (18.85.0.105,3975) (0 bytes).
README
compact.tar.Z
full.tar.Z
hrtfdoc.ps
hrtfdoc.txt
226 Transfer complete.
60 bytes received in 0.42 seconds (0.14 Kbytes/s)
ftp> binary
200 Type set to I.
ftp> get README
200 PORT command successful.
150 Opening data connection for README (18.85.0.105,3806) (417 bytes).
226 Transfer complete.
local: README remote: README
952 bytes received in 0.043 seconds (22 Kbytes/s)

etc.

```

Please note that there are no files shared between the two tar archive files. To expand the tar archives, use:

```

kdm@eno:~ > uncompress full.tar.Z
kdm@eno:~ > tar xvf full.tar
kdm@eno:~ > uncompress compact.tar.Z
kdm@eno:~ > tar xvf compact.tar

```

This will create the directories ``full'' and ``compact''.

To retrieve the HRTF data via the WWW, use your browser to open the following URL:

<http://sound.media.mit.edu/KEMAR.html>

Simply follow the directions found in the html document.

Usage restrictions

This HRTF data is Copyright 1994 by the MIT Media Lab. It is provided without any usage restrictions. We request that you cite the authors when using this data for research or commercial applications.

Correspondence

All correspondence regarding this data should be directed to:

Keith Martin	Bill Gardner
MIT Media Lab, E15-401D	MIT Media Lab, E15-401B
20 Ames Street	20 Ames Street
Cambridge, MA 02139	Cambridge, MA 02139

<http://sound.media.mit.edu/KEMAR/hrtfdoc.txt>

8/8/2000

kdm@media.mit.edu

billg@media.mit.edu

Acknowledgements

The successful completion of this project would not have been possible without the help and support of W. M. Rabinowitz, J. G. Desloge, Abhijit Kulkarni, and the MIT Media Lab Machine Listening Group. This research is supported in part by the MIT Media Laboratory and the National Science Foundation.

Bibliography

- [1] A. V. Oppenheim and R. W. Schaffer. Discrete-Time Signal Processing. Prentice-Hall, Englewood Cliffs, NJ, 1989.
- [2] D. D. Rife and J. Vanderkooy. ``Transfer-Function Measurements using Maximum-Length Sequences''. J. Audio Eng. Soc., 37(6):419-444, June 1989.
- [3] J. Vanderkooy. ``Aspects of MLS Measuring Systems''. J. Audio Eng. Soc., 42(4):219-231, April 1994.

<http://sound.media.mit.edu/KEMAR/hrtfdoc.txt>

8/8/2000

HRTF Measurements of a KEMAR Dummy-Head Microphone
MIT Media Lab Perceptual Computing - Technical Report #280

Bill Gardner and Keith Martin
MIT Media Lab
May, 1994

abstract

An extensive set of head-related transfer function (In this document, we use the acronym HRTF to refer to head related impulse responses. The impulse response and transfer function are related in the obvious way by the Fourier transform.) measurements of a KEMAR dummy head microphone has recently been completed. The measurements consist of the left and right ear impulse responses from a Realistic Optimus Pro 7 loudspeaker mounted 1.4 meters from the KEMAR. Maximum length (ML) pseudo-random binary sequences were used to obtain the impulse responses at a sampling rate of 44.1 kHz. In total, 710 different positions were sampled at elevations from -40 degrees to +90 degrees. Also measured were the impulse response of the speaker in free field and several headphones placed on the KEMAR. This data is being made available to the research community on the Internet via anonymous FTP and the World Wide Web.

Measurement technique

Measurements were made using a Macintosh Quadra computer equipped with an Audiomedia II DSP card, which has 16-bit stereo A/D and D/A converters that operate at a 44.1 kHz sampling rate. One of the audio output channels was sent to an amplifier which drove a Realistic Optimus Pro 7 loudspeaker. This is a small two way loudspeaker with a 4 inch woofer and 1 inch tweeter. The KEMAR, Knowles Electronics model DB-4004, was equipped with model DB-061 left pinna, model DB-065 (large red) right pinna, Etymotic ER-11 microphones, and Etymotic ER-11 preamplifiers. The outputs of the microphone preamplifiers were connected to the stereo inputs of the Audiomedia card.

From the standpoint of the Audiomedia card, a signal sent to the audio outputs results in a corresponding signal appearing at the audio inputs. Measuring the impulse response of this system yields the impulse response of the combined system consisting of the Audiomedia D/A and A/D converters and anti-alias filters, the amplifier, the speaker, the room in which the measurements are made, and most importantly, the response of the KEMAR with its associated microphones and preamps. We can avoid interference due to room reflections by ensuring that any reflections occur well after the head response time, which is several milliseconds. We can compensate for a non-uniform speaker response by measuring the speaker response separately and creating an inverse filter. The inverse filter, when applied to an HRTF measurement, equalizes the speaker response to be flat.

The impulse responses were obtained using ML sequences (for a detailed description of the ML sequence measurement technique, see [2]). The sequence length was $N = 16383$ samples, corresponding to a 14-bit generating register. Two copies of the sequence were concatenated to form a $2*N$ sample sound which was played from the Audiomedia card. Simultaneously, $2*N$ samples were recorded on both the left and right input channels (we wrote software for the Audiomedia to simultaneously play and record stereo sounds). For each input channel, the following

<http://sound.media.mit.edu/KEMAR/hrtfdoc.txt>

8/8/2000

technique was used to recover the impulse response. The first N samples of the result were discarded, and the remaining N samples were duplicated to form a $2*N$ sample sequence. This was cross-correlated with the original N sample ML sequence using FFT based block convolution, forming a $3*N - 1$ sample result. The N sample impulse response was extracted starting at $N - 1$ samples into this result.

Noise in the ML sequence impulse responses can be attributed to measurement noise, non-linearities in the system, and time aliasing. Measurement noise can be averaged out by using longer ML sequences. This is completely analogous to averaging smaller length measurements. For instance, averaging two independent N point impulse response measurements should achieve a 3 dB signal to noise ratio (SNR) improvement over either of the measurements considered alone. Similarly, using a $2*N(+1)$ point ML sequence should achieve a 3 dB SNR improvement over using an N point ML sequence. However, noise caused by non-linearities in the system will not be reduced by repeated averaging over ML sequence measurements, because the noise is correlated between measurements. It is necessary either to use longer ML sequences or to average the responses resulting from different ML sequences (i.e. from different masks) to reduce noise caused by non-linearities (see [3]). Time aliasing can be eliminated by using ML sequences which are longer than the reverberation time of the measurement space. Since the measurements were done in an anechoic chamber and the ML sequences were sufficiently long, time aliasing was not a problem. We chose 16383 point measurements to give good signal to noise ratios without excessive storage requirements or computation time. The measured SNR was 65 dB, as discussed later.

Measurement procedure

The measurements were made in MIT's anechoic chamber. The KEMAR was mounted upright on a motorized turntable which could be rotated accurately to any azimuth under computer control. The speaker was mounted on a boom stand which enabled accurate positioning of the speaker to any elevation with respect to the KEMAR. Thus, the measurements were made one elevation at a time, by setting the speaker to the proper elevation and then rotating the KEMAR to each azimuth. With the KEMAR facing forward toward the speaker (0 degrees azimuth), the speaker was positioned such that a normal ray projected from the center of the face of the speaker bisected the interaural axis of the KEMAR at a distance of 1.4 meters. This was accomplished using a tape measure, plumb line, calculator, a 1.4 meter rod, and a fair amount of eyeballing. We believe the speaker was always within 0.5 inch of the desired position, which corresponds to an angular error of ± 0.5 degrees.

The spherical space around the KEMAR was sampled at elevations from -40 degrees (40 degrees below the horizontal plane) to +90 degrees (directly overhead). At each elevation, a full 360 degrees of azimuth was sampled in equal sized increments. The increment sizes were chosen to maintain approximately 5 degree great-circle increments. The table below shows the number of samples and azimuth increment at each elevation (all angles in degrees). A total of 710 locations were sampled.

Elevation	Number of Measurements	Azimuth Increment
-40	56	6.43

<http://sound.media.mit.edu/KEMAR/hrtfdoc.txt>

8/8/2000

-30	60	6.00
-20	72	5.00
-10	72	5.00
0	72	5.00
10	72	5.00
20	72	5.00
30	60	6.00
40	56	6.43
50	45	8.00
60	36	10.00
70	24	15.00
80	12	30.00
90	1	x.xx

Table 1: Number of measurements and azimuth increment at each elevation

If the KEMAR was perfectly symmetrical and its ear microphones were identical, we would only need to sample either the left or right hemisphere around the KEMAR. However, our KEMAR had two different pinnae (the left pinna was "normal", the right pinna was the "large red" model), and consequently the responses were not identical. This was actually a bonus, because by sampling the entire sphere we obtained two complete sets of symmetrical HRTFs.

Speaker and headphone measurements

The impulse response of the Optimus Pro 7 speaker was measured in the anechoic chamber using a Neumann KMi 84 microphone at a distance of 1.4 meters. The measurement technique was exactly the same as the HRTF measurements. The speaker impulse response can be used to create an inverse filter to equalize the HRTF measurements, as will be discussed later.

In addition to measuring the speaker response, we also measured a variety of headphones placed on the KEMAR. The headphones measured are listed in Table 2.

AKG K240	Circumaural, closed earcups, but not well isolated.
Sennheiser HD480	Supraaural, open air.
Radio Shack Nova 38	Supraaural, walkman style.
Sony Twin Turbo	Intraaural, earplug style.

Table 2: Description of headphones measured

It is possible the HRTF data will be used to create a spatial auditory display, in which case the frequency response of the headphones used to render the display is important. The above headphone responses may be useful to create appropriate inverse filters. We did not gather data on the repeatability of such measurements (i.e. how much variation in the frequency response is expected each time the headphones are placed on the head).

The data

As described earlier, each HRTF measurement yielded a 16383 point impulse response at a 44.1 kHz sampling rate. Most of this data is irrelevant. The 1.4 meter air travel corresponds to approximately 180 samples, and there is an additional delay of 50 samples inherent in

<http://sound.media.mit.edu/KEMAR/hrtfdoc.txt>

8/8/2000

the playback/recording system. Consequently, in each impulse response, there is a delay of approximately 230 samples before the head response occurs. The head response persists for several hundred samples (subject to interpretation) and is followed by various reflections off objects in the anechoic chamber (such as the KEMAR turntable). In order to reduce the size of the data set without eliminating anything of potential interest, we decided to discard the first 200 samples of each impulse response and save the next 512 samples. Each HRTF response is thus 512 samples long. Most researchers will no doubt truncate this data further.

The impulse responses are stored as 16-bit signed integers, with the most significant byte stored in the low address (i.e. Motorola 68000 format). The dynamic range of the 16-bit integers (96 dB) exceeds the signal to noise ratio of the measurements, which we conservatively measured to be 65 dB. Using the 0 degree elevation, 0 degree azimuth, left ear, 16383 point measurement, we compared the energy in 100 samples centered on the head response to the first 100 samples of the response (these should ideally be zero) which yielded the 65 dB SNR.

The HRTF data is stored in directories by elevation. Each directory name has the format ``elevEE'', where EE is the elevation angle. Within each directory each filename has the format ``XEEeAAAa.dat'' where X is either ``L'' or ``R'' for left and right ear response, respectively, EE is the elevation angle of the source in degrees, from -40 to 90, and AAA is the azimuth of the source in degrees, from 0 to 355. Elevation and azimuth angles indicate the location of the source relative to the KEMAR, such that elevation 0 azimuth 0 is directly in front of the KEMAR, elevation 90 is directly above the KEMAR, elevation 0 azimuth 90 is directly to the right of the KEMAR, etc. For example, the file ``R-20e270a.dat'' is the right ear response, with the source 20 degrees below the horizontal plane and 90 degrees to the left of the head. Note that three digits are always given for azimuth so that the files appear in sorted order in each directory.

To select a pair of HRTF responses, we recommend using symmetrical responses obtained from one of the KEMAR ears. For instance, for the HRTF responses for a source 45 degrees to the right of the head at 0 degrees elevation, use ``L0e045a.dat'' for the left ear and ``L0e315a.dat'' for the right ear, or use ``R0e315a.dat'' for the left ear and ``R0e045a.dat'' for the right ear. Note that this approach eliminates binaural localization cues in the median plane.

The maximum sample value in the left ear HRTF data is -26793 in file ``L40e289a.dat''. In the right ear HRTF data the maximum value is 29877 in the file ``R40e039a.dat''.

The speaker impulse response and headphone impulse responses are stored in the directory ``headphones+spkr''. An inverse filter for the Optimus Pro 7 speaker is included. The inverse filter was designed by zero-padding the measured impulse response and taking the DFT of the zero-padded sequence. The resulting complex spectrum was inverted by negating the phase and inverting the magnitude. This was done over the range from DC to 18 kHz; beyond 18 kHz the inverse spectrum was made flat by repeating the 18 kHz magnitude value. The inverse filter was obtained by computing the inverse DFT of this spectrum. A minimum phase version of this inverse filter was also computed using the real cepstrum (see [1]). The files in the ``headphones+spkr'' directory are listed in Table 3.

filename	description
Optimus.dat	Optimus Pro 7 impulse response
Opti_inverse.dat	Inverse filter for Optimus Pro 7
Opti_minphase.dat	Minimum phase inverse filter
AKG-K240-L.dat	AKG headphone impulse response
AKG-K240-R.dat	
Senn-HD480-L.dat	Sennheiser headphone impulse response
Senn-HD480-R.dat	
RS-Nova38-L.dat	Radio Shack headphone impulse response
RS-Nova38-R.dat	
Sony-TwinTurbo-L.dat	Sony headphone impulse response
Sony-TwinTurbo-R.dat	

Table 3: Contents of ``headphones+spkr'' directory

The 512 point impulse responses and speaker and headphone data may be found in the tar archive ``full.tar.Z''.

Compact data files

For those interested purely in 3-D audio synthesis, we have included a data-reduced set of 128 point symmetrical HRTFs derived from the left ear KEMAR responses. These have also been equalized to compensate for the non-uniform response of the Optimus Pro 7 speaker. The 128 point responses may be found in the tar archive ``compact.tar.Z''. The data-reduced impulse responses are stored in directories by elevation as described above. Within each directory each filename has the format ``HEEeAAAa.dat'' where EE is the elevation angle of the source in degrees, and AAA is the azimuth angle of the source in degrees.

Each file contains a stereo pair of 128 point impulse responses corresponding to the left and right ear responses for the given source position. For instance, the file ``H0e090a.dat'' contains the left and right ear impulse responses for a source directly to the right of the listener. The left response was derived from the 512 point file ``L0e090a.dat'' and the right response was derived from the 512 point file ``L0e270a.dat''. The data is stored as 16-bit integers and the stereo samples are stored in (left, right) interleaved order. Each 128 point response was obtained by convolving the appropriate 512 point impulse responses with the minimum phase inverse filter for the Optimus Pro 7 speaker. The resulting impulse responses were then cropped by retaining 128 samples starting at sample index 26. The maximum sample value in the 128 point data is 30496 in the file ``H-10e100a.dat''.

Accessing the data on the Internet

The data is organized into two tar archives, this document (postscript and plain text) and a text README file. The structure of the tar archives is described in the previous sections.

To retrieve the HRTF data by anonymous FTP, your FTP session would look something like the following:

```
kdm@eno:~ > ftp sound.media.mit.edu
Connected to sound.media.mit.edu.
220 sound.media.mit.edu FTP server (ULTRIX Version 4.1 Tue Mar 19 00:38:17 EST 1991
Name (sound.media.mit.edu:kdm): anonymous
331 Guest login ok, send ident as password.
```

<http://sound.media.mit.edu/KEMAR/hrtfdoc.txt>

8/8/2000

```

Password: {Type your User ID here}
230 Guest login ok, access restrictions apply.
ftp> cd pub
250 CWD command successful.
ftp> cd Data
250 CWD command successful.
ftp> cd KEMAR
250 CWD command successful.
ftp> ls
200 PORT command successful.
150 Opening data connection for /bin/ls (18.85.0.105,3975) (0 bytes).
README
compact.tar.Z
full.tar.Z
hrtfdoc.ps
hrtfdoc.txt
226 Transfer complete.
60 bytes received in 0.42 seconds (0.14 Kbytes/s)
ftp> binary
200 Type set to I.
ftp> get README
200 PORT command successful.
150 Opening data connection for README (18.85.0.105,3806) (417 bytes).
226 Transfer complete.
local: README remote: README
952 bytes received in 0.043 seconds (22 Kbytes/s)

etc.

```

Please note that there are no files shared between the two tar archive files. To expand the tar archives, use:

```

kdm@eno:~ > uncompress full.tar.Z
kdm@eno:~ > tar xvf full.tar
kdm@eno:~ > uncompress compact.tar.Z
kdm@eno:~ > tar xvf compact.tar

```

This will create the directories ``full'' and ``compact''.

To retrieve the HRTF data via the WWW, use your browser to open the following URL:

<http://sound.media.mit.edu/KEMAR.html>

Simply follow the directions found in the html document.

Usage restrictions

This HRTF data is Copyright 1994 by the MIT Media Lab. It is provided without any usage restrictions. We request that you cite the authors when using this data for research or commercial applications.

Correspondence

All correspondence regarding this data should be directed to:

Keith Martin	Bill Gardner
MIT Media Lab, E15-401D	MIT Media Lab, E15-401B
20 Ames Street	20 Ames Street
Cambridge, MA 02139	Cambridge, MA 02139

or

<http://sound.media.mit.edu/KEMAR/hrtfdoc.txt>

8/8/2000

kdm@media.mit.edu

billg@media.mit.edu

Acknowledgements

The successful completion of this project would not have been possible without the help and support of W. M. Rabinowitz, J. G. Desloge, Abhijit Kulkarni, and the MIT Media Lab Machine Listening Group. This research is supported in part by the MIT Media Laboratory and the National Science Foundation.

Bibliography

- [1] A. V. Oppenheim and R. W. Schaffer. Discrete-Time Signal Processing. Prentice-Hall, Englewood Cliffs, NJ, 1989.
- [2] D. D. Rife and J. Vanderkooy. ``Transfer-Function Measurements using Maximum-Length Sequences''. J. Audio Eng. Soc., 37(6):419-444, June 1989.
- [3] J. Vanderkooy. ``Aspects of MLS Measuring Systems''. J. Audio Eng. Soc., 42(4):219-231, April 1994.

<http://sound.media.mit.edu/KEMAR/hrtfdoc.txt>

8/8/2000